

Project Name\_\_\_\_

\_Date\_\_

Type or Model \_\_\_\_\_

\_Qty \_\_\_


# **AMP<sup>®</sup> Low Voltage Landscape Lighting** Single Source LED MR16 Color Lamp- MR16-35-RGBCW1

### **PRODUCT DESCRIPTION**

Introducing the first ever VOLT® RGBCW LED MR16 bulb – our first replaceable color-changing LED bulb. Effortlessly choose from a wide spectrum of colors, adjust the brightness, control the color temperature (warm 2200K to crisp, bright 4000K), or set up to 6 zones all through the RF remote (sold separately).

Ideal for applications where balanced, multi-colored illumination is desired. Designed and optimized to fit all current MR16 fixtures.

### **PRODUCT DIMENSIONS**





# SPECIFICATIONS

- ▶ Input Voltage: 11-16V, 50/60Hz AC
- Beam Angles: 38° or 60° beam spreads
- Correlated Color Temperature (CCT): 2200K, 2700K, 3000K, 4000K
- Color Rendering Index (CRI): > 80
- Operating Voltage: 12VAC
- Powered by: AMP's Low Voltage Transformer
- Watts: 6W
- Lumens: 260 at 2200K | 300 at 4000K

# **FEATURES & BENEFITS**

- Replacements for 35W Halogen MR16 lamps
- ▶ 38° or 60° beam spreads
- Requires AMP® RF Remote Control (sold separately) for usage. One remote controls all AMP® RGBCW lamps.
- Designed and optimized for compatibility with all current MR16 fixtures.
- RGB + Cool White to Warm White
- Dimmable

# WARRANTY

Residential: Lifetime Warranty Commercial: 10-Year Warranty